



DIAGRAM CIRCUIT. MERCURY FIVE

REF No.	RESISTORS.	PART No.	REF No.	CONDENSERS.	PART No.	REF No.	MISCELLANEOUS.	PART No.
R1, 2	56k	R418	C1,12,15	16+32+32 μ F 200V/A	C83	J1, 2	JACK SOCKETS	S133
R3,7,9	1M	R39	C2,16	.1 μ F	C29	F1	FUSE 1A	F16
R4	470k	R32	C3,14,18	50 μ F 25v	C327	S1	MAINS SWITCH	
R5,8	100k	R27	C4,7	.01 μ F 400v	C220	S2	FOOT SWITCH	S410
		R15	C5	250pt	C284	S3	SOCKET SINGLE WAY AERIAL	S4
		R23	C6,13	.005 μ F	C219	P1	PLUG	P18
R11,24	47k	R35	C8	2 μ F	C195	T1	TRANSFORMER MAINS 246-0-246V	T7
R12,13,14	680k	R4	C9,10,11	.002 μ F	C28	T2	" " OUTPUT, ELAC	T110
R15	100 Ω	R16	C19	.03 μ F	C223	V1	VALVE EF86	V77
R16	5k	R166	C21	.02 μ F	C506	V2	" " ECC83	V11
R17	150 Ω	R386	C20	.01 μ F 100v	C335	V3	" " EL84	V76
R18	250 Ω	R360	VC1	.5M Semi log	P254	V4	" " EZ80	V75
R19	3.3M	R30	VC2	1M Semi log	P22	V5	" " EM 88	V56
R21	220k	R42	VC3	2.5M Linear	P9			
R22	2.2M	R246	VC4	.5M antilog	P93			
R23	510k							
R24	500k							
R26	2.7M							

PRG. No. 2022 Z
PART No. D45.